GE Fanuc Embedded Systems



QPMC-1553

High Density PMC Module

Features

- 1, 2 or 4 independent MIL-STD-1553 dual redundant channels
- · Multi-function features
 - Simultaneous bus controller, 31 remote terminals and bus monitor
- Single-function features
 - Bus controller or 31 remote terminals or bus monitor
- Bus Controller BC
 - BC->RT, RT->BC, RT->RT
 - Mode codes, broadcast and single-shot messaging
 - Programmable time delays
 - Major/minor frames
 - Real-time conditional branching
 - Two aperiodic messaging methods
- Remote Terminal RT
 - RT data wrapping
 - Multiple RT buffers
 - Dynamic bus control
 - Automatic mode code and status bit responses
 - Programmable response time
 - RT map monitoring

- Bus Monitor BM
 - Full error detection
 - Multiple monitoring methods
 - 45-bit time-tagging
- Adv. interrupts and triggers
- Architecture
 - BC & RT error injection/detection
 - FPGA architecture
 - BC & RT link list structures
 - 1 Mbyte RAM per channel
 - Direct & transformer coupling
 - Environmental options
- Software support
 - Advanced, high-level API
 - Source code included
 - BusTools Analyzer optional

GE Fanuc Embedded Systems' QPMC-1553 provides new levels of performance and flexibility for MIL-STD-1553A/B Notice II on a PMC (PCI Mezzanine Card) module. Available in commercial, ruggedized and conductively cooled versions with one, two or four dual-redundant channels, the QPMC-1553 includes advanced API (Application Programming Interface) software that reduces application development time.

Standard features include selectable transformer or direct coupling, 1 Mbyte of RAM per channel, 45-bit message timetagging, triggers, extensive BC and RT link-list structures, error injection/ detection, avionics level discretes, automatic/ manual RT Status Bit and Mode Code responses, along with advanced BC functionality. An IRIG-B signal Receiver/Generator with GPS synchronization, variable voltage output and 66 MHz PCI bus operation are optionally available. With the highest speed encoder/decoder in the industry, the QPMC-1553 Bus Monitors provide unparalleled error detection and 100% monitoring of fully loaded buses.

Multi-function Interfaces

QPMC-1553 multi-function interfaces are easily configured to operate with simultaneous Bus Controller, 31 Remote Terminals and Bus Monitor functionality.

Single-function Interfaces

Single-function QPMC-1553 interfaces have all the features and functionality of the multi-function versions, but only one major operational mode is enabled at a time. Each interface can emulate either a Bus Controller or 31 Remote Terminals or Bus Monitor.

Software

GE Fanuc Embedded Systems provides our advanced 1553 API in source code, along with support for Windows XP, 2000, Me, NT, 98, 95, Linux, LynxOS, VxWorks and other operating systems. To access 1553 functionality without software development, *BusTools*/1553, GE Fanuc Embedded Systems' MIL-STD-1553 bus analysis, simulation and data logging/monitoring solution is available.



QPMC-1553 High Density PMC Module

Specifications

Physical

- PMC Mezzanine Card (74 mm x 149 mm without bezel)
- Standard configuration has front bezel I/O

Environmental

- Standard operating temperature range: 0°C to +70°C
- Relative humidity: 5 to 90% (non-condensing)
- Optional ruggedized, extended temp and conductively cooled configurations

Software Support

- API High-level libraries with source code included for Windows XP, 2000, Me, NT, 98, 95, Linux, LynxOS and VxWorks
- GUI Optional BusTools/1553 GUI Bus Analyzer (multi-function boards only)

Connections

- · Direct or transformer coupling
- I/O triggers; 18 avionics-level discretes
- Front panel bezel or P14 I/O connections
- Transition cabling to 1553 cable jacks included on front panel configurations

Multi-function Operational Modes

Simultaneous BC, 31 RTs and BM

Single-function Operational Modes

. BC or 31 RTs or BM

Power (4 channels at 75% duty cycle)

- +5 VDC @ 1.3 A (typ.)
- +3 3 VDC @ 150 mA
- 7.2 W power dissipated on board

On-board Shared RAM

• 1 Mbyte (per dual-redundant channel)

PCI Signal Compatibility

- Universal (5V or 3.3V)
- Optional 66 MHz PCI bus operation

Configuration Options

- 1, 2 or 4 dual-redundant channels
- Optional P14 I/O
- Optional ruggedized, -40°C to +85°C operating temperature range
- Optional ruggedized, VITA compliant conductive cooling (max +71°C rail temp)
- Optional conformal coating
- · Optional IRIG-B Receiver (AM or DC/TTL) and
- Generator (DC/TTL)
- Available mounted on a PCI, 3U/6U CompactPCI carrier board

Description

Bus Controller

- · Programmable control over:
 - Major and minor frame content and timing
 - Intermessage gap times
 - Response time-out and late response
- Multiple BC retry
- Modify messages, data or setup while card is running
- · Insert aperiodic messages into a running BC list
- "Oneshot" mode for simplified BC operation
- Conditional message sequencing based on real-time message data or status
- Selectable interrupt generation and status messages on full range of system conditions or all detected errors

- Late response

- Early response

- No response

- Full error detection
 - Invalid word
 - Bit count error
 - High word
 - Low word - Inverted sync
- Incorrect RT addressParity error
 - Manchester
- Extensive programmable error injection (on a per word basis)
- · Synchronize BC operation to external trigger source

Remote Terminal

- Multiple RT simulation (up to 31 RTs)
- Programmable error injection (on a per word basis)
- Modify data, status words or setup while card is running
 Programmable message content (linked message
- buffers)Interrupts can be generated on a per message basis
- upon End of Message and error conditions
- RT Map Monitoring

Bus Monitor

- Capture 100% fully loaded bus traffic with:
- Time-tagging Error status
- Word status Message status
- RT response time
- Interrupts can be selected by RT/SA/WC
- Extensive filtering and triggering options
- By individual RT/subaddress
- Transmit, receive or broadcast mode codes
- Internal or external triggering
- Trigger output on user specified data
- Real-time bus playback with RT edit mode
- 45-bit, microsecond resolution timetagging
- IRIG/GPS synchronization

Ordering Information

OPMC-1553-1M

MIL-STD-1553 multi-function, single dual-redundant channel, fixed voltage PMC interface

OPMC-1553-2M

 ${\tt MIL-STD-1553\ multi-function,\ two\ dual-redundant\ channel,\ fixed\ voltage\ PMC\ interface}$

QPMC-1553-4M

MIL-STD-1553 multi-function, four dual-redundant channel, fixed voltage PMC interface QPMC-1553-1S

MIL-STD-1553 single-function, single dual-redundant channel, fixed voltage PMC interface

QPMC-1553-2S
MIL-STD-1553 single-function, two dual-redundant channel, fixed voltage PMC interface

QPMC-1553-4S

MIL-STD-1553 single-function, four dual-redundant channel, fixed voltage PMC interface Contact Factory for Conduction Cooled, Rugged and Other Configurations

About GE Fanuc Embedded Systems

GE Fanuc Embedded Systems is a leading global provider of embedded computing solutions for a wide range of industries and applications. Our comprehensive product offering includes many types of I/O, single board computers, high performance signal processors, fully integrated, rugged systems including flat panel displays, plus high speed networking and communications products. The company is head-quartered in the U.S. and has design, manufacturing and support offices throughout the world. Whether you're looking for one of our standard products or a fully custom solution, GE Fanuc Embedded Systems has the breadth, experience and 24/7 support to deliver what you need. For more information, visit www.gefanucembedded.com.

GE Fanuc Embedded Systems Information Centers

Americas:

1 800 322 3616 or 1 256 880 0444

Asia Pacific: 86 10 6561 1561

Europe, Middle East and Africa: +49 821 5034-0

©2007 GE Fanuc Embedded Systems. All rights reserved.
All other brands or names are property of their respective holders.
Specifications are subject to change without notice.

Additional Resources

For more information, please visit the GE Fanuc Embedded Systems web site at:

www.gefanucembedded.com

